



SOFTWARE UPGRADE

The latest version of software for the Spec Ops Elite HP5 Ultra series camera is: Q03311F

IMPORTANT: During the software installation, your camera can not be powered off via the power switch, or lose battery supply voltage via weak batteries, or ejecting the battery tray. If any of these events occur, your camera may no longer be functional. Your camera will need to be returned to our warranty center to have the software reloaded on our production line equipment. Before you begin your new software installation, please insert new alkaline AA batteries in your camera. Please follow the instructions below to upgrade the software on your trail camera. If you have any questions or need assistance with upgrading your camera software, you can contact us at 1-888-618-4496, Option 2.

STEP 1 :Place the .BRN file for your model on a blank SD card, **do not open the file**. Read the instructions fully before proceeding with the update. Model# BTC-8E-HP5U uses the file named brnbtc83.BRN.

STEP 2: With the camera powered OFF insert this SD card in the SD card slot in your camera.

STEP 3: Power ON your trail camera, do not allow your camera to take a picture or video and place it on the SD card with the upgrade. Press the MODE button to enter the cameras Menu. Press E to enter CAMERA SETUP Press the UP arrow button once to get to the 'FW Upgrade' setting. Press E to enter the setting.

Change No to Yes using the arrow buttons and press E to begin the update.

The cameras display will read "Upgrading" for approximately 30 seconds while the upgrade is being performed. During this period, do not turn the camera off, or eject the battery tray. When the software upgrade is complete, the cameras display will go blank and then return you to the cameras Home Screen. The factory settings of the camera will have been restored as well as the date and time so you will want to reset them.